

ROG Claymore Core

- **Conectividad Tecnológica**

Wired, USB 2.0

- **Soporte OS**

Windows® 10

Windows® 8.1

Windows® 7

- **Dimensiones**

360 x 145 x 45 mm

- **Peso**

770 g with cable

- **Contenidos**

1 x Claymore Core keyboard

1 x USB cable

1 x ROG pouches

2 x ROG logo stickers

User documentation

- **Nota**

[Hot Keys]

Profile switch:

Fn + 1/ 2 / 3/ 4/ 5/ 6: Profile 1 - 6 (6 is default profile)

Lighting effects switch:

Fn + Right or Fn + Left

Brightness level:

Fn + Up: Brightness up (5 levels)

Fn + Down: Brightness down (5 levels)

Color customization:

Fn + Delete: Red increase (10 levels)

Fn + End: Green increase (10 levels)

Fn + PageDown: Blue increase (10 levels)

ROG SYNC (sync Aura lighting effects between Claymore and Aura-enabled mouse):

Fn + PrintScreen

*Only available when Armoury software is activated.

*Synchronization will take about 10 seconds.

Motherboard fan speed control:

Fn + "+" or Fn + "-"

*Only available when Fan Xpert software and Armoury software are activated.

On-the-fly macro recording:

Step 1: Fn + Right-ALT to start recording

Step 2: Fn + Right-ALT to end recording

Step 3: assign Macro Key

Windows key lock:

Fn + Windows key

*Not available under Armoury software Claymore lighting page.

Repeat acceleration:

Fn + F1: 1X

Fn + F2: 2X

Fn + F3: 3X

Fn + F4: 4X

Overclocking & Booting-up Hot Keys (ROG KeyBot II S5 mode)

Boot-up: Long press on ENTER

Boot-up and overclock CPU: Long press F11

Boot-up and overclock memory: Long press F12

Boot-up and enter BIOS: Long press DELETE

Clear CMOS: C + L + R

*Please plug keyboard to the dedicated USB socket found on your ROG motherboard.

*Only available when KeyBot II software is activated and switched on.